

# Grid Pad Specifications July 2016



	Go	Rugged	Pro 11	Pro 13	Pro 18	Eye 11 <small>(with Alea Intelligaze camera)</small>	Eye 13 <small>(with Alea Intelligaze camera)</small>	Eye 18 <small>(with Alea Intelligaze camera)</small>
Operating System	Windows 10	Windows 8.1	Windows 10	Windows 10	Windows 10	Windows 10	Windows 10	Windows 10
Included software	Grid 3	Grid 3	Grid 3	Grid 3	Grid 3	Grid 3	Grid 3	Grid 3
Processor	Intel Atom 1.6GHz	Intel Atom 1.33GHz	Intel Core 0.8GHz	Intel Celeron 1.40GHz	Intel Pentium Quad Core 1.6GHZ	Intel Core 0.8GHz	Intel Celeron 1.40GHz	Intel Pentium Quad Core 1.6GHZ
Memory	4GB	2GB	4GB	8GB	8GB	4GB	8GB	8GB
Hard drive	64GB	64GB	128GB	256GB SSD	500GB	128GB	256GB SSD	500GB
Dimensions (mm)	228 x 150 x 13	270 x 185 x 20	310 x 200 x 50	344 x 216 x 57	440 x 325 x 50	310 x 260 x 70	344 x 216 x 70	440 x 325 x 70
Weight (kg)	0.5	0.84	1	2.68	2.75	1.7	3	3
Battery life	Up to 10hrs	Up to 6hrs	Up to 6hrs 20	Up to 8hrs - plus hot swap battery	Up to 4hrs 40	Up to 2hrs 30 with eye gaze	Up to 6 hours with eye gaze - plus hot swap battery	Up to 2hrs with eye gaze
Screen	8.3" 1080p	10.1" 800p	11.6" 1080p	13.3" 1080p	17.3" 1080p	11.6" 1080p	13.3" 1080p	17.3" 1080p
Eye gaze camera	n/a	n/a	n/a	n/a	n/a	Alea IntelliGaze or MyGaze 2	Alea IntelliGaze or MyGaze 2	Alea IntelliGaze or MyGaze 2
Ports	1 x USB 2.0, Micro SD, 3.5mm Speaker Out	2 x USB2.0, 3.5mm speaker out, Micro HDMI, Micro SD card slot	2 x USB2.0, 1 x USB3.0, 3.5mm Speaker Out, Micro SD, Micro HDMI, Auditory Feedback Port	2 x USB 2.0, 3.5mm Speaker Out, Mic in, Auditory Feedback Port	2 x USB 2.0, 3.5mm Speaker Out, USB 3.0, HDMI, Micro SD, Auditory Feedback Port	2 x USB2.0, 1 x USB3.0, 3.5mm Speaker Out, Micro SD, Micro HDMI, Auditory Feedback Port	2 x USB 2.0, 3.5mm Speaker Out, Mic in, Auditory Feedback Port	2 x USB 2.0, 3.5mm Speaker Out, USB 3.0, HDMI, Micro SD, Auditory Feedback Port
Switch access	Bluetooth or via USB Joycable	Bluetooth or via USB Joycable	2 x 3.5mm jacks radio switch (additional extra)	2 x 3.5mm jacks radio switch (additional extra)	2 x 3.5mm jacks radio switch (additional extra)	2 x 3.5mm jacks radio switch (additional extra)	2 x 3.5mm jacks radio switch (additional extra)	2 x 3.5mm jacks radio switch (additional extra)
Amplified speaker	Bluetooth speaker	Bluetooth speaker	2 x built-in high quality speakers	2 x built-in high quality speakers	2 x built-in high quality speakers	2 x built-in high quality speakers	2 x built-in high quality speakers	2 x built-in high quality speakers
Mounting	n/a	n/a	Rehadapt and Daessy compatible	Rehadapt and Daessy compatible	Rehadapt and Daessy compatible	Rehadapt and Daessy compatible	Rehadapt and Daessy compatible	Rehadapt and Daessy compatible
Environment control	Via Wi-fi	Via Wi-fi	Servus inside - Gewa, Eldat or Z-wave radio switch receiver	Servus inside - Gewa, Eldat or Z-wave radio switch receiver	Servus inside - Gewa, Eldat or Z-wave radio switch receiver	Servus inside - Gewa, Eldat or Z-wave radio switch receiver	Servus inside - Gewa, Eldat or Z-wave radio switch receiver	Servus inside - Gewa, Eldat or Z-wave radio switch receiver